

1/4" Dia. x 5/8" to 1" length ferrule fuses

AGA-V (axial leads)

AGA

Specifications

Description: Fast-acting fuse.

Dimensions:

1/4" x 5/8"
(6.4 x 15.9mm).

Construction:

Glass tube.

Ratings:

Volts — 125Vac (or less)

Amps — 1/6-30A

IR — 10,000 (1/16-1 1/2A @ 125Vac)

— 200A (2-5A @ 125Vac)

— 1000A (6-30A @ 32Vac)

Agency Information: CE, Std. 248-14, UL File E19180, UL Listed, Guide JDYX 0-1 1/2A UL Recognized, Guide JDYX2 2-12A.

Features and Benefits

- Fast-acting for maximum protection.
- Size rejects insertion of other fuse types.

Typical Applications

- Electronic Circuits

Catalog Numbers (Amps) With Axial Leads*

AGA-V-1/16	AGA-V-1	AGA-V-7 1/2
AGA-V-1/10	AGA-V-1 1/2	AGA-V-10
AGA-V-1/8	AGA-V-2	AGA-V-15
AGA-V-1/4	AGA-V-2 1/2	AGA-V-20
AGA-V-3/8	AGA-V-3	AGA-V-25
AGA-V-1/2	AGA-V-5	AGA-V-30
AGA-V-5/16	AGA-V-6	
AGA-V-3/4	AGA-V-7	

Without Axial Leads

AGA-1/16	AGA-1	AGA-7 1/2
AGA-1/10	AGA-1 1/2	AGA-10
AGA-1/8	AGA-2	AGA-15
AGA-1/4	AGA-2 1/2	AGA-20
AGA-3/8	AGA-3	AGA-25
AGA-1/2	AGA-5	AGA-30
AGA-5/16	AGA-6	
AGA-3/4	AGA-7	

*AGA-V is UL Listed 0-5A, UL Recognized 6-12A.

AGW

Specifications

Description: Fast-acting fuse.

Dimensions: 1/4" x 7/8"
(6.4 x 22.2mm).

Construction: Glass tube.

Ratings:

Volts — 32Vac

Amps — 1-30A

IR — 100A

Features and Benefits

- Fast-acting for maximum protection.
- Size rejects insertion of other fuse types.

Typical Applications

- Electronic Circuits

Catalog Numbers (Amps)

AGW-1	AGW-4	AGW-15
AGW-1 1/2	AGW-5	AGW-20
AGW-2	AGW-6	AGW-25
AGW-2 1/2	AGW-7 1/2	AGW-30
AGW-3	AGW-10	



AGX-V (axial leads)

AGX

Specifications

Description: Fast-acting fuse.

Dimensions: 1/4" x 1"
(6.4 x 25.4mm).

Construction: Glass tube.

Ratings:

Volts — 250Vac (1/500-2A)

— 125Vac (2 1/2-7A)

— 32V (8-30A)

Amps — 1/500-30A

IR — 35A (1/500-2A @ 250Vac)

— 10,000A (2 1/2-7A @ 125Vac)

— 1000A (8-30A @ 32V)

Agency Information: CE, Std. 248-14, UL File E19180 UL Listed, Guide JDYX, 0-5A UL Recognized, Guide JDYX2, 6-20A CSA File 47233; Class 1422-01, 0-5A.

Features and Benefits

- Size rejects insertion of other fuse types.

Typical Applications

- Electronic Circuits

Catalog Numbers (Amps) With Axial Leads**

AGX-V-1/500	AGX-V-1/2	AGX-V-5
AGX-V-1/250	AGX-V-1/10	AGX-V-6
AGX-V-1/100	AGX-V-1/2	AGX-V-7
AGX-V-1/50	AGX-V-3/4	AGX-V-8
AGX-V-1/16	AGX-V-1	AGX-V-10
AGX-V-1/10	AGX-V-1 1/4	AGX-V-15
AGX-V-1/8	AGX-V-1 1/2	AGX-V-20
AGX-V-1/4	AGX-V-2	AGX-V-25
AGX-V-3/16	AGX-V-2 1/2	AGX-V-30
AGX-V-1/4	AGX-V-3	
AGX-V-3/16	AGX-V-4	

Without Axial Leads

AGX-1/500	AGX-1/2	AGX-5
AGX-1/250	AGX-1/10	AGX-6
AGX-1/100	AGX-1/2	AGX-7
AGX-1/50	AGX-3/4	AGX-8
AGX-1/16	AGX-1	AGX-10
AGX-1/10	AGX-1 1/4	AGX-15
AGX-1/8	AGX-1 1/2	AGX-20
AGX-1/4	AGX-2	AGX-25
AGX-3/16	AGX-2 1/2	AGX-30
AGX-1/4	AGX-3	
AGX-3/16	AGX-4	

**AGX-V is UL Recognized from 6-20A @ 32Vac

