

Fluke i5sPQ3, 5 A AC Current Clamps, 3-pack

Three current clamps configured to provide accurate low current measurements on secondary current transformers without breaking the circuit. Buy Online Now.



Fluke i5sPQ3 5 A AC Current Clamps, 3-pack



Model Name	Description
i5sPQ3	i5sPQ3, 5 A ac Current Clamps, 3-pack

Three current clamps configured to provide accurate low current measurements on secondary current transformers without breaking the circuit. Buy Online Now.



- Overview
- Features
- Specifications
- Models and Accessories
- More Info

Specifications	
Nominal current range	5 A
Continuous current range	10 mA to 6 A
Maximum Non-Destructive Current	70 A
Lowest measurable current	10 mA
Basic Accuracy	<div style="display: flex; justify-content: space-between;"> <div style="width: 40%;"></div> <div style="width: 55%;"> 48 Hz to 65 Hz 10 mA to 1 A 1% + 5 mA 1 A to 5 A 1% </div> </div>
Useable frequency	40 Hz to 5 kHz
Output level(s)	400 mV/A
Input Load Impedance	> 1 MΩ in parallel with up to 47 pF
Crest Factor	≤ 3, add 0.7% to accuracy

Safety Specifications	
Safety	CAT III 600 V per IEC/EN61010-1, Pollution Degree 2
Maximum voltage	600 V ac

Mechanical & General Specifications	
Warranty	1 year
Maximum conductor diameter	15 mm
Output cable length	2.5 m
BNC Adapter	Yes
BNC to banana adapter included	No