



*Representative photograph,
actual product appearance
may vary.*

*Due to regional agency
approval requirements, some
products may not be available
in your area. Please contact
your regional Honeywell
office regarding your product
of choice.*

2TP1-61

**TP Series Rocker Switch, 2 pole, 3 position, Screw terminal,
Flush Panel Mounting**

Features

- Environmentally sealed
- Two and three-position pushbutton action
- Various button colors
- 1, 2, and 4-pole circuitry
- Flush panel and above panel mountings
- Temperature range: -54 °C to +71 °C [-65 °F to +160 °F]
- UL recognized, CSA certified
- CE approved

Typical Applications

- Industrial machinery and equipment
- Military and commercial aviation
- Marine applications
- Construction equipment
- Test instruments
- Agricultural machinery
- Process control
- Medical instrumentation

Description

TP Rocker switches may be mounted flush with panel for a low-button profile or above panel for a distinct button appearance. Buttons measure 22,1 mm x 37,1 mm [.87 in x 1.46 in]. They are removable and interchangeable, and come in transparent plastic, translucent plastic, and six colors of opaque plastic. Switches without buttons are also available, as well as separate buttons.



2TP1-61

TP Series Rocker Switch, 2 pole, 3 position, Screw terminal, Flush Panel Mounting

Product Specifications	
Product Type	Rocker
Ampere / Voltage Range (Resistive Load)	0.5 A at 250 Vdc, 0.5 A to 10 A at 0.5 Vac to 277 Vac, 0.5 A to 18 A at 0.5 Vdc to 28 Vdc, 0.75 A at 115 Vdc
Circuitry	DPST
Action	3 position
Circuitry/Operating action	
Mounting	Flush Panel
Termination	Screw
Button Type	Translucent
UL/CSA Rating Code	L192: 10 A-125, 250, 277 Vac; 1/4 Hp-125 Vac; 1/2 Hp-250, 277 Vac; 3 A-125 Vac "L"
Comment	Silver cadmium oxide contacts
Availability	Global
UNSPSC Code	302119
UNSPSC Commodity	302119 Switches and controls and relays
Series Name	TP Series



2TP1-61

TP Series Rocker Switch, 2 pole, 3 position, Screw terminal, Flush Panel Mounting

WARNING

PERSONAL INJURY

DO NOT USE these products as safety or emergency stop devices, or in any other application where failure of the product could result in personal injury.

Failure to comply with these instructions could result in death or serious injury.

WARNING

MISUSE OF DOCUMENTATION

- The information presented in this product sheet (or catalog) is for reference only. DO NOT USE this document as product installation information.
- Complete installation, operation and maintenance information is provided in the instructions supplied with each product.

Failure to comply with these instructions could result in death or serious injury.

© Copyright Honeywell Inc. 1998-2004 All rights reserved.