

Please be informed that the data shown in this PDF Document is generated from our Online Catalog. Please find the complete data in the user's documentation. Our General Terms of Use for Downloads are valid (http://phoenixcontact.com/download)



HEAVYCON socket insert, B24 series, 24 + PE-pos., push-in connection

#### **Product Features**

- For fast coding with plastic profile



# **Key Commercial Data**

| Packing unit                         | 1 pc     |
|--------------------------------------|----------|
| Weight per Piece (excluding packing) | 120.0 g  |
| Custom tariff number                 | 85366990 |
| Country of origin                    | China    |

## Technical data

### General

| Connection method            | Push-in connection   |
|------------------------------|--|
| Degree of pollution          | 3  |
| Overvoltage category         | III  |
| Number of positions          | 24+PE  |
| Insertion/withdrawal cycles  | ≥ 500  |
| Туре                         | B24  |
| Conductor cross section      | 0.14 mm² 2.5 mm²   |
| Connection cross section AWG | 26 14  |
| Stripping length             | 8 mm 10 mm   |
| Assembly instructions        | Coding also using the CP-HC (1686478) coding profiles. HC-B6/ HC-B10for two coding profiles. HC-B16/ HC-B24for four coding profiles. |



## Technical data

#### General

| Connection | Connectors may only be operated when there is no load/the power is switched off. Can be used for solid wires and stranded wires with ferrule. |
|------------|---|
|            |   |

#### Ambient conditions

| Ambient temperature (operation) | -40 °C 125 °C (including heating up of contacts) |
|---------------------------------|--|
|                                 | , , ,  |

#### Material data

| Flammability rating according to UL 94 | V0  |
|--|---|
| Contact material                       | Copper alloy  |
| Contact surface material               | Ag/Sn (tarnish protection)  |
| Contact carrier material               | PA  |
| Standards/regulations                  | PA: Fire protection in rail vehicles - requirement sets R22 and R23 acc. to DIN EN 45545-2 (Risk level HL1 - HL2) |
|  | PA: Fire protection in rail vehicles - requirement set R24 acc. to DIN EN 45545-2 (Risk level HL1 - HL3)          |

#### Electrical characteristics

| Rated voltage (III/3) | 500 V |
|-----------------------|-------|
| Rated surge voltage   | 6 kV  |
| Rated current         | 16 A  |

## Standards and Regulations

| Flammability rating according to UL 94 | V0 |
|--|----|

# Classifications

## eCl@ss

| eCl@ss 4.0 | 272607xx |
|------------|----------|
| eCl@ss 4.1 | 27260701 |
| eCl@ss 5.0 | 27143424 |
| eCl@ss 5.1 | 27143424 |
| eCl@ss 6.0 | 27143424 |
| eCl@ss 7.0 | 27440205 |
| eCl@ss 8.0 | 27440205 |
| eCl@ss 9.0 | 27440205 |

## **ETIM**

| ETIM 3.0 | EC000438 |
|----------|----------|
| ETIM 4.0 | EC000438 |
| ETIM 5.0 | EC000438 |



# Classifications

## UNSPSC

| UNSPSC 6.01   | 30211923 |
|---------------|----------|
| UNSPSC 7.0901 | 39121522 |
| UNSPSC 11     | 39121522 |
| UNSPSC 12.01  | 39121522 |
| UNSPSC 13.2   | 39121522 |

# Approvals

| Αr | מכ | rov | ′als |
|----|----|-----|------|
|    |    |     |      |

Approvals

CSA / UL Recognized / EAC / EAC / GL

Ex Approvals

Approvals submitted

## Approval details

| CSA 1              |       |  |
|--------------------|-------|--|
|                    |       |  |
| mm²/AWG/kcmil      | 14    |  |
| Nominal current IN | 10 A  |  |
| Nominal voltage UN | 600 V |  |

| UL Recognized <b>5</b> |       |  |  |  |
|------------------------|-------|--|--|--|
|                        |       |  |  |  |
| mm²/AWG/kcmil          | 14    |  |  |  |
| Nominal current IN     | 13 A  |  |  |  |
| Nominal voltage UN     | 600 V |  |  |  |



# Approvals


| EAC |  |  |
|-----|--|--|
|     |  |  |


EAC

GL

## **Drawings**

#### Schematic diagram







Derating diagram for 2.5 mm<sup>2</sup>


Connector pin assignment, connection side

### Dimensional drawing





### Dimensional drawing



Mounting cutout when used without housing

Phoenix Contact 2016 © - all rights reserved http://www.phoenixcontact.com

Dimensional drawing