

8360 SERIES

360° NON-CONTACTING THROUGH-HOLE POSITION SENSOR

Introduction

The 8360 Series is latest addition to the company's line-up of robust, reliable, and highly accurate non-contacting position sensors. The 8360's low profile and throughhole design make it desirable for applications like steering wheel and boom angle, where space is limited and the sensor must mount around a shaft. The sensor's dual analog output is capable of resolving 360 degrees of motion with high accuracy and 12 bit resolution.

The 8360 Series provides IP65 sealing, 360 degree continuous rotation, a robust package and wide operating temperature range, making it especially well suited for applications with harsh environments like industrial vehicles, agricultural and construction equipment and process controls. Non-contacting, redundant outputs provide the high reliability and long life that are an absolute necessity in applications such as medical equipment or wind/solar energy applications. A wide range of adaptations are available including PWM or Can Bus output, shaft interface, electrical angle, connector type, cable length, output slope and much more.



Features

- Non-contacting technology: Provides long life
- Output signal choices: Analog, PWM, CAN Bus
- **Electrical angle:** The standard version is available with rotational angles in 15 degree increments, up to 360°
- **Connector**: Flying lead terminated w/6 pin AMP connector P/N 776434-1, contact P/N 1924463-1, other options available
- Through-hole design: Fits around shaft, shaft options available
- Environmental: IP65-protected from dust and water jets
- Operating temperature: -40°C to 125°C
- Electrical protection: Overvoltage, short circuit, ESD
- Magnetic Shielding to 20G



Mechanical

Mechanical travel	Travel 0° to +360° with no stops, allowing for 360 degree continuous rotation			
Actuation (starting) Torque	0.2 N-m (28.5 oz-in) Weight 220 grams max.			
Rotational Life	10 million revolutions			


Flectrical

Electrical Angle	15° to 360° in 15 degree increments standard (other options available)				
Input Voltage	5.0 V±0.25V DC				
Input Current	16mA maximum per output 32mA maximum total (both channels)				
Sensor Output	0.25V – 4.75V for Analog at 5.0V input				
Accuracy	+/- 0.6%				
Resolution	12 Bit, 0.088 degree				


Page 1

Environmental

Environmental Sealing	IP65 standard			
Electromagnetic Compatibility	100V/meter, 15kHz — 1GHz range			
Vibration	10 – 10,000 Hz, Total PSD: 4.94 Grms			
Shock	50Gs, half sine pulse, 11 m sec duration			
Operating temperature range	-40°C to 125°C			
Storage temperature range	-40°C to +105°C			



DIMENSIONS






Rotor Interface is 12 tooth spline						
Pitch Angle	30°					
Diametral Pitch	16/32					
Pitch Diameter	19.05					
Largest Diameter	20.3 ± 0.1					
Smallest Diameter	16.5 ± 0.5/-0					
(Ref ANSI B92.1 - 1970 Tol. Class B)						





OUTPUT FUNCTION



ACTIVE ELECTRICAL ANGLE



CONNECTOR

Connector Pin Layout									
PIN#	1	2	3	4	5	6			
Pinout	Voltage Supply	Output 1	GND	Voltage Supply	Output 2	GND			
Color	Red	White	Black	Yellow	Green	Brown			

Page 3

Sensata Technologies, Inc. ("Sensata") data sheets are solely intended to assist designers ("Buyers") who are developing systems that incorporate Sensata products (also referred to herein as "components"). Buyer understands and agrees that Buyer remains responsible for using its independent analysis, valuation, and judgment in designing Buyer's systems and products. Sensata data sheets have been created using standard laboratory conditions and engineering practices. Sensata has not conducted any testing other than that specifically described in the published documentation for a particular data sheet. Sensata may make corrections, enhancements, improvements, and other changes to its data sheets or components without notice.

Buyers are authorized to use Sensata data sheets with the Sensata component(s) identified in each particular data sheet. HOWEVER, NO OTHER LICENSE, EXPRESS OR IMPLIED, BY ESTOPPEL OTHERWISE TO ANY OTHER SENSATA INTELLECTUAL PROPERTY RIGHT, AND NO LICENSE TO ANY THIRD PARTY TECHNOLOGY OR INTELLECTUAL PROPERTY RIGHT, IS GRANTED HEREIN. SENSATA DATA SHEETS ARE PROVIDED "AS IS". SENSATA MAKES NO WARRANTIES OR REPRESENTATIONS WITH REGARD TO THE DATA SHEETS OR USE OF THE DATA SHEETS, EXPRESS, IMPLIED, OR STATUTORY, INCLUDING ACCURACY OR COMPLETENESS. SENSATA DISCLAIMS ANY WARRANTY OF TITLE AND ANY IMPLIED WARRANTIES OF MERCHANTABILITY, FITNESS FOR A PARTICULAR PURPOSE, QUIET ENJOYMENT, QUIET POSSESSION, AND NON-INFRINGEMENT OF ANY THIRD PARTY INTELLECTUAL PROPERTY RIGHTS WITH REGARD TO SENSATA DATA SHEETS OR USE THEREOF.

All products are sold subject to Sensata's terms and conditions of sale supplied at www.sensata.com SENSATA ASSUMES NO LIABILITY FOR APPLICATIONS ASSISTANCE OR THE DESIGN OF BUYERS' PRODUCTS. BUYER ACKNOWLEDGES AND AGREES THAT IT IS SOLELY RESPONSIBLE FOR COMPLIANCE WITH ALL LEGAL, REGULATORY, AND SAFETY-RELATED REQUIREMENTS CONCERNING ITS PRODUCTS, AND ANY USE OF SENSATA COMPONENTS IN ITS APPLICATIONS, NOTWITHSTANDING ANY APPLICATIONS-RELATED INFORMATION OR SUPPORT THAT MAY BE PROVIDED BY SENSATA.

Mailing Address: Sensata Technologies, Inc., 529 Pleasant Street, Attleboro, MA 02703, USA

CONTACT US

America

+1 (800) 350 2727 sensors@sensata.com **Europe, Middle East & Africa**

+33 (3) 88 20 8080 position-info.eu@sensata.com

Asia Pacific

sales.isasia@list.sensata.com China +86 (21) 2306 1500 Japan +81 (45) 277 7117 Korea +82 (31) 601 2004 India +91 (80) 67920890 Rest of Asia +886 (2) 27602006 ext 2808