

_

Cable Glands Accessories

Multi-Hole Cable Gland Inserts



Multi-Hole Cable Gland Inserts | IP65 Rating



Mencom Multi-Hole Cable Gland Inserts will allow the user to use one cable gland for multiple wires, cables, or tubes. The inserts fit into the Mencom "MCG" or "PCG" cable glands, and will seal to IP65.

Part Number	# of Holes	Diameter of Holes mm (inches)	Fits Into	
M25-0x0	0	None	MCG-3/4 MCG-3/4R	MCG-M25
M25-2x8	2	8 (0.315)		
M25-3x4	3	4 (0.157)		
M25-3x7	3	7 (0.276)		
M25-4x5	4	5 (0.197)		
M25-4x6.5	4	6.5 (0.256)		
M32-2X8	2	8 (0.315)	MCG-1.0	MCG-M32
M32-3X8	3	8 (0.315)		
M32-4X7	4	7 (0.276)		
M32-4X8	4	8 (0.315)		
M32-4X8.5	4	8.5 (0.335)		
M32-6X4	6	4 (0.157)		
M32-6X6	6	6 (0.236)		
M40-0X0	0	None	- MCG-1.25 MCG-M40	
M40-4X10	4	10 (0.394)		
M40-5X8.5	5	8.5 (0.335)		MCG-M40
M40-8X6.5	8	6.5 (0.256)		

Inserts are intended for use with wires, cables, or tubes that have diameters that are within ±0.020" of the "hole diameter" listed. Inserts without holes allow the user to drill holes for low volume, custom applications.

Inserts can be pre-installed in cable glands for orders of 100 or more. Order as follows:

Multi-Hole Insert PG 11-3X3 Desired Cable Gland MCG-11 Resulting Part Number MCG-11-3X3