



Plug in relay, Type N, relay socket, 8 tubular pin, single tier, for 8501KP relays and 9050JCK timers

8501NR51

Product availability: Stock - Normally stocked in distribution facility

Main

[In] rated current 15 A 300 V AC 5 A 600 V AC

Complementary

mounting type	DIN rail Panel	
electrical connection	Single tiered screw clamp terminals	
package quantity	1	
Width	1.6 in (40 mm)	
Height	2.1 in (54 mm)	
Depth	1.0 in (24.6 mm)	

Ordering and shipping details

Category	US10CP221142
Discount Schedule	0CP2
GTIN	785901583592
Returnability	Yes
Country of origin	US

Packing Units

Unit Type of Package 1	PCE	
Number of Units in Package 1	1	
Package 1 Height	1.00 in (2.540 cm)	
Package 1 Width	1.70 in (4.318 cm)	
Package 1 Length	2.20 in (5.588 cm)	
Package 1 Weight	1.600 oz (45.359 g)	
Unit Type of Package 2	CAR	
Number of Units in Package 2	600	
Package 2 Height	14.20 in (36.068 cm)	
Package 2 Width	11.20 in (28.448 cm)	
Package 2 Length	17.80 in (45.212 cm)	
Package 2 Weight	64.0002 lb(US) (29.030 kg)	

Price is "List Price" and may be subject to a trade discount – check with your local distributor or retailer for actual price.

Contractual warranty

Warranty

18 months

Mar 1, 2025



Schneider Electric aims to achieve Net Zero status by 2050 through supply chain partnerships, lower impact materials, and circularity via our ongoing "Use Better, Use Longer, Use Again" campaign to extend product lifetimes and recyclability.

Environmental Data explained >

How we assess product sustainability >

⊘ Environmental footprint		
Carbon footprint (kg CO2 eq, Total Life cycle)	1	

Use Better

⊗ Materials and Substances	
Packaging made with recycled cardboard	No
Packaging without single use plastic	No
China RoHS Regulation	China RoHS declaration
California proposition 65	WARNING: This product can expose you to chemicals including: Nickel compounds, which is known to the State of California to cause cancer, and Di-isodecyl phthalate (DIDP), which is known to the State of California to cause birth defects or other reproductive harm. For more information go to www.P65Warnings.ca.gov

Use Again

○ Repack and remanufacture	
Circularity Profile	No need of specific recycling operations
Take-back	No