This announcement is based on product catalogue information previously shown before its discontinuation.

Product information of the existing product may be different from this version.

# **MOS FET Relays**

G3VM-355J/JR

New MOS FET Relays with Both SPST-NO and SPST-NC Contacts Incorporated in a Single SOP Package. General-purpose Models Added.

- SPST-NO/SPST-NC models with an 8-pin SOP package now available in the 350-V load voltage series.
- Continuous load current of 120 mA (90 mA).
- Dielectric strength of 1,500 Vrms between I/O.
- General-purpose models (models with high ON resistance) added to the series.

#### **RoHS** compliant

Refer to "Common Precautions".

## **■** Application Examples

- Broadband systems
- · Measurement devices
- · Data loggers
- · Amusement machines



**Note:** The actual product is marked differently from the image shown here.

## **■** List of Models

Contact form	Terminals	Load voltage (peak value)	Model	Number per stick	Number per tape
		350 VAC	G3VM-355JR	50	
SPST-NC	terminals		G3VM-355J		
			G3VM-355JR(TR)		2,500
			G3VM-355J(TR)		


### **■** Dimensions

Note: All units are in millimeters unless otherwise indicated.

G3VM-355J/JR




Note: The actual product is marked differently from the image shown here.




## ■ Terminal Arrangement/Internal Connections (Top View)

G3VM-355J/JR



# ■ Actual Mounting Pad Dimensions (Recommended Value, Top View)

G3VM-355J/JR



Product information of the existing product may be different from this version.

# ■ Absolute Maximum Ratings (Ta = 25°C)

	Item	Symbol	Rating	Unit	Measurement Conditions	
Input	put LED forward current		50	mA		
	Repetitive peak LED forward current	I <sub>FP</sub>	1	Α	100 μs pulses, 100 pps	
	LED forward current reduction rate	Δ I <sub>F</sub> /°C	-0.5	mA/°C	Ta ≥ 25°C	
	LED reverse voltage	$V_R$	5	V		
	Connection temperature	Tj	125	°C		
Output	Output dielectric strength	V <sub>OFF</sub>	350	V		
	Continuous load current	I <sub>O</sub>	120 (90)	mA		
	ON current reduction rate	Δ I <sub>ON</sub> /°C	-1.2 (-0.9)	mA/°C	Ta ≥ 25°C	
	Connection temperature	Tj	125	°C		
	ic strength between input and See note 1.)	V <sub>I-O</sub>	1,500	Vrms	AC for 1 min	
Operati	Operating temperature		-40 to +85	°C	With no icing or condensation	
Storage	Storage temperature		-55 to +125	°C	With no icing or condensation	
Solderin	ng temperature (10 s)		260	°C	10 s	


Note: 1. The dielectric strength between the input and output was checked by applying voltage between all pins as a group on the LED side and all pins as a group on the light-receiving side.

VM-355J/

Values in parentheses are for the G3VM-355J.

## **■** Electrical Characteristics (Ta = 25°C)

					•		•		
	Item		Symbol	Mini- mum	Typical	Maxi- mum	Unit	Measurement conditions	
In- put	LED forward voltage		$V_{F}$	1.0	1.15	1.3	٧	I <sub>F</sub> = 10 mA	
	Reverse current		I <sub>R</sub>			10	μА	V <sub>R</sub> = 5 V	
	Capacity between terminals		C <sub>T</sub>		30		pF	V = 0, f = 1 MHz	
	Trigger LED forward current		I <sub>FT</sub>		1	3	mA	SPST-NO: I <sub>O</sub> = 90 mA	
			I <sub>FC</sub>					SPST-NC: I <sub>OFF</sub> = 10 μA	
Out- put	Maximum resistance with output ON		R <sub>ON</sub>		15 (40)	25 (50)	Ω	SPST-NO: $I_F = 5 \text{ mA}$ , $I_O = 90 \text{ mA}$	
								SPST-NC: $I_F = 0 \text{ mA}$ , $I_O = 90 \text{ mA}$	
	Current leakage when the relay is open		I <sub>LEAK</sub>			1.0	μΑ	V <sub>OFF</sub> = 350 V	
Capa	Capacity between I/O terminals		C <sub>I-O</sub>		0.8		pF	f = 1 MHz, Vs = 0 V	
Insulation resistance		R <sub>I-O</sub>	1,000			ΜΩ	V <sub>I-O</sub> = 500 VDC, RoH ≤ 60%		
Turn-ON time		SPST-NO	tON		(0.3)	1.0	ms	$I_F$ = 5 mA, $R_L$ = 200 Ω,	
		SPST-NC			(0.25)	1.0	ms	V <sub>DD</sub> = 20 V (See note 2.)	
Turn-OFF time		SPST-NO	tOFF		(0.15)	1.0	ms		
		SPST-NC			(0.5)	3.0 (1)	ms		



Values in parentheses are for the G3VM-355J.

## ■ Recommended Operating Conditions

Use the G3VM under the following conditions so that the Relay will operate properly.


Item	Symbol	Minimum	Typical	Maximum	Unit
Output dielectric strength	$V_{DD}$			280	V
Operating LED forward current	I <sub>F</sub>	5		25	mA
Continuous load current	I <sub>O</sub>			120 (90)	mA
Operating temperature	Ta	-20		65	°C

Values in parentheses are for the G3VM-355J.

## **■** Engineering Data

#### **Load Current vs. Ambient Temperature**

#### G3VM-355J/JR



## **■** Safety Precautions

Refer to "Common Precautions" for all G3VM models.